

PSPSeq 3.01 (very) Quick Start Guide

to select a location to trigger a note... press the digital pad up, down, left, or right (to move one step at a time) or analog pad up, down, left, or right (move 8 steps left/right or 1 step up/down).

to trigger a note... press the X button.

to delete a triggered note... press and hold the X button and then left trigger or hold X and move the D-pad down until TRIG is equal to 0.

to change the volume of a selected note... hold X and press the analog pad or digital pad left or right.

to mute or unmute a track... press the square button.

to change the volume of an entire track... hold O and press the analog pad or digital pad up or down.

to change the pan of a specific triggered step... hold O and press the analog pad or digital pad left or right.

to change the pan of all notes in a track... hold O and right trigger and press the analog pad or digital pad left or right.

to modify basic synth parameters from the sequencer... hold triangle and either left trigger or right trigger (for slow and fast modifications) and press either the analog or digital pad up or down.

to change loops... press either left or right trigger.

to start/stop the sequencer, choose LOOP or SONG modes, change the BPM, or the output volume... press SELECT to access the transport and the digital pad left or right to highlight the appropriate option. BPM and volume are controlled by pressing the analog and digital pads up/down and starting or stopping the sequencer and LOOP/SONG modes are controlled by pressing the digital pad up/down.

to access the menu system... press START.

to load a song.... press START, select SYSTEM, press X or digital pad right, select LOAD, press X or digital pad right, select the song to load and press X or digital pad right.

to access synthesizer and FX parameters... press START, select SYNTH, select EDIT SYNTH, select the track to modify, select either GEN (for the generator portion) or FX (for the FX portion) or ENV (for the output envelope). to immediately jump to the GEN/FX/ENV menu for the current step press triangle + left trigger + right trigger.

to modify synthesizer parameters.... press the analog pad up or down (left trigger and right trigger modify rate of change) or the digital pad up/down while holding either the left or right trigger. to change all parameters in a loop hold triangle while performing the operations above. to move between triggered steps press the analog pad left or right. to randomize a parameter go to the start point, set a lower bound and press X, then move to the end point, set the upper bound and press X again.